

# Bollard Light D

## GLI-BLLD

### INSTALL AND MAINTENANCE MANUAL

#### WARNING

1. Read all instructions.
2. Install in accordance with national and local electrical code regulations.
3. This product is intended to be installed and serviced by a qualified, licensed electrician.
4. Turn off electrical power before installing or servicing luminaire in any way.
5. To reduce the risk of fire and overheating, make sure all connections are tight.



**May result in serious injury or death.  
Turn power OFF at circuit breaker  
prior to installation or servicing.**

### WARNINGS AND CAUTIONS

- **Electrical Safety:** Disconnect power at the circuit breaker before installation or maintenance to avoid electric shock.
- **Qualified Personnel:** Installation must be performed by a licensed electrician in compliance with local codes.
- **Voltage Verification:** Ensure the supply voltage matches the fixture's specifications to prevent damage.
- **Secure Mounting:** Verify that the mounting surface or structure can support the weight of the fixture.
- **Wiring Precautions:** Ensure all wiring connections are properly insulated and secure to prevent hazards.
- **Heat Dissipation:** Ensure adequate clearance around the fixture to allow for proper heat dissipation and prevent overheating.
- **Environmental Conditions:** Suitable for both indoor and outdoor use. Ensure the installation environment is free of corrosive substances.
- **Avoid Exposure:** Do not install the fixture in areas prone to prolonged submersion or extreme environmental conditions unless specifically rated for such use.
- **Safety Handling:** Do not carry, lift, or hold the fixture by the power cable to prevent product damage and potential injury.

# GLI-BLLD Bollard Light D Installation Instructions

## INSTALLATION

1. Thread the J-bolts into the bracket plate.
2. Place the bracket plate with J-bolts into the new concrete pour.
3. If J-bolts were not pre-installed, insert studs into the ground at the appropriate location.
4. Separate the fixture from the base plate by removing the bottom screws.
5. Place the base plate over the J-bolts or studs.
6. Secure the base plate by tightening the nuts onto the J-bolts or studs.
7. Bring the wiring to the fixture through the base plate.
8. Connect the fixture wires according to the labels on the wires, ensuring all connections are waterproof.
9. Align the screw holes and base tabs, then place the fixture onto the base.
10. Insert the screws and tighten them securely.

